

MOTOR AMP DRAW

<u>BLOWER</u>	<u>H.P.</u>	<u>VOLT</u>	<u>IDLE</u>	<u>FULL LOAD</u>
THREE PHASE MOTORS				
BD-7	3/4	208	2.7	3.2
BD-7	3/4	230	2.4	3.0
BD-7	3/4	460	1.2	1.5
BD-8	1	208	2.7	3.7
BD-8	1	230	2.4	3.6
BD-8	1	460	1.2	1.8
BD-9	1 1/2	208	3.1	4.4
BD-9	1 1/2	230	2.8	4.0
BD-9	1 1/2	460	1.4	2.0
BD-11 & BD-12	2	208	4.9	5.9
BD-11 & BD-12	2	230	4.4	5.6
BD-11 & BD-12	2	460	2.2	2.8
BD-13 & BD-14	3	208	6.2	8.8
BD-13 & BD-14	3	230	5.6	8
BD-13 & BD-14	3	460	2.8	4.0
BD-15, 16 & 17	5	208	8.8	14
BD-15, 16 & 17	5	230	8.0	13.8
BD-15, 16 & 17	5	460	4.0	6.9

<u>BLOWER</u>	<u>H.P.</u>	<u>VOLT</u>	<u>IDLE</u>	<u>FULL LOAD</u>
---------------	-------------	-------------	-------------	------------------

SINGLE PHASE MOTORS				
BD-7	3/4	115	9.6	10.2
BD-7	3/4	208	5.3	5.4
BD-7	3/4	230	4.8	5.1
BD-8	1	115	9	12.4
BD-8	1	208	5	6.5
BD-8	1	230	4.5	6.2
BD-9	1 1/2	115	11.4	17.8
BD-9	1 1/2	208	6.3	9.3
BD-9	1 1/2	230	5.7	8.9
BD-11 & BD-12	2	115	14	20.4
BD-11 & BD-12	2	208	7.7	11.1
BD-11 & BD-12	2	230	7	10.2
BD-13 & BD-14	3	115	18	32
BD-13 & BD-14	3	208	10	16.8
BD-13 & BD-14	3	230	9	16.0
BD-15, 16 & 17	5	115	-	N/A
BD-15, 16 & 17	5	208	14.9	25
BD-15, 16 & 17	5	230	13.5	23.0

<u>R.P.M</u>
1725
1725
1725
1725
1725
1725
3450
3450
3450
1725
1725
1725
1725
1725
1725
1725
1725
1725
<u>R.P.M</u>

1725
1725
1725
1725
1725
1725
3450
3450
3450
1725
1725
1725
1725
1725
1725
1725
1725
1725